

AHD/CVI/TVI to HDMI & VGA & CVBS Converter

Model: DA-HD303



Feature:

- Support TVI and AHD/CVI standard, Including 720P/30, 720P/25, 1080P/30, 1080P/25, NTSC/PAL 960H camera input.
- AHD/TVI/CVI to CVBS (AV)—it can be locked CVBS signal is 576I/50Hz or 480I/60Hz output automatically, the CVBS NTSC/PAL format adjustable.
- AHD/TVI/CVI to HDMI—it supports the max HDMI 1080P@50/60Hz adjustable.
- AHD/TVI/CVI to VGA—it supports the max VGA 1920*1080 automatically, the VGA output support 800*600/60Hz、1024*768/60Hz、1280*720/60Hz、1280*1024/60Hz、1360*768/60Hz、1920*1080/60Hz
- AHD/TVI/CVI input can be auto detected AHD/TVI/CVI signal is NTSC or PAL

There are 2 switches:

Switch 1: Output signal selection

A、When HDMI output, switch 1 can select 720P/60 or 1080P/60

B、When VGA output, switch 1 can select 1024*768/60Hz、1280*720/60Hz、1280*1024/60Hz、1360*768/60Hz、1920*1080/60Hz

C、When CVBS output, switch 1 can select NTSC or PAL format.

Switch 2: Output mode selection

Select HDMI、VGA、CVBS output

- Built-in ESD protect circuit
- Built-in industrial level surge protector

Specification:

Input interface	AHD/TVI/CVI
Output interface	CVBS/HDMI/VGA
Power consumption	DC 12V / 500mA $\pm$ 10%
Humidity	30%~85%
Storage temperature	-10 °C ~ 85 °C
Dimension	110(W) x 85(L) x 28(H)
Weight	160g

Packing:

1. AHD/CVI/TVI to HDMI & VGA & AV Converter **x1**
2. USER MANUAL x1